

## Control and signaling units Ø 22

Harmony Easy XA2, plastic  
Pushbuttons, switches and pilot lights: complete units

### Functions (continued)

#### Contact functions (continued)

##### Selector or key switches, 2 or 3-position



Type of push	Standard handle	Long handle	Key
Degree of protection	IP 54	IP 54	IP 54
Reference	<b>XA2ED**</b>	<b>XA2EJ**</b>	<b>XA2EG21/EG*3</b>
Pages	11		

#### Combined functions: contact and signaling

##### Illuminated pushbuttons, spring return



Type of push	Flush push
Degree of protection	IP 54
LED	Integral LEDs, 24, 220-230 or 380-400 V
Color	White, Green, Red, Yellow, and Blue
Reference	<b>XA2EW3*51/3*M11/3*Q1</b>
Pages	12

#### Signaling functions

##### Pilot lights



Degree of protection	IP 40
LED	Integral LEDs, 24, 110, 220-230 or 380-400 V
Color	White, Green, Red, Yellow, and Blue
Reference	<b>XB7EV**LC/IEV*De/LC</b>
Pages	13

References:  
page 9

8

Schneider  
Electric

### References

## Control and signaling units Ø 22

Harmony Easy XA2, plastic  
Spring return pushbuttons, marked and unmarked  
Mushroom head pushbuttons, spring return



#### Spring return pushbuttons with flush push

Shape of head	Type of contacts	Color of push	Marking	Reference	Weight kg/lb
Unmarked		White	—	<b>XA2EA11</b>	0.032/0.071
		Black	—	<b>XA2EA21</b>	0.032/0.071
		Green	—	<b>XA2EA31</b>	0.032/0.071
		Yellow	—	<b>XA2EA51</b>	0.032/0.071
		Blue	—	<b>XA2EA61</b>	0.032/0.071
		Red	—	<b>XA2EA42</b>	0.032/0.071
Marked		Green	"I"	<b>XA2EA3311</b>	0.032/0.071
		Black	"↑"	<b>XA2EA3351</b>	0.032/0.071
		White	"↑"	<b>XA2EA3341</b>	0.032/0.071
		Red	"O"	<b>XA2EA4322</b>	0.032/0.071
		Red	"STOP"	<b>XA2EA4342</b>	0.032/0.071

#### Mushroom head pushbuttons, spring return

Shape of head	Type of contacts	Color of push	Diameter Ø (mm)/in.	Reference	Weight kg/lb
		Black	40/1.575	<b>XA2EC21</b>	0.052/0.115
		Green	40/1.575	<b>XA2EC31</b>	0.052/0.115
		Red	40/1.575	<b>XA2EC42</b>	0.052/0.115
		Yellow	40/1.575	<b>XA2EC51</b>	0.052/0.115
		Black	60/2.362	<b>XA2ER21</b>	0.058/0.128

Note: Please refer to our website [www.schneider-electric.com](http://www.schneider-electric.com) for information on dimensions

General:  
page 6

Schneider  
Electric

9