

## Control and signaling units Ø 22

Harmony Easy XA2, plastic  
Pushbuttons, switches and pilot lights: complete units

**Functions (continued)**

**Contact functions (continued)**

**Selector or key switches, 2 or 3-position**



Type of push	Standard handle	Long handle	Key
Degree of protection	IP 54	IP 54	IP 54
Reference	<b>XA2ED**</b>	<b>XA2EJ**</b>	<b>XA2EG21/EG*3</b>
Pages	11		

**Combined functions: contact and signaling**

**Illuminated pushbuttons, spring return**



Type of push	Flush push
Degree of protection	IP 54
LED	Integral LEDs, 24, 220-230 or 380-400 V
Color	White, Green, Red, Yellow, and Blue
Reference	<b>XA2EW3*51/3*M1/3*Q1</b>
Pages	12

**Signaling functions**

**Pilot lights**



Degree of protection	IP 40
LED	Integral LEDs, 24, 110, 220-230 or 380-400 V
Color	White, Green, Red, Yellow, and Blue
Reference	<b>XB7EV**LC/IEV*De/LC</b>
Pages	13

References:  
page 9

References

## Control and signaling units Ø 22

Harmony Easy XA2, plastic  
Spring return pushbuttons, marked and unmarked  
Mushroom head pushbuttons, spring return

**Spring return pushbuttons with flush push**

Shape of head	Type of contacts	Color of push	Marking	Reference	Weight kg/lb
<b>Unmarked</b>					
	1 -	White	-	<b>XA2EA11</b>	0.032/0.071
		Black	-	<b>XA2EA21</b>	0.032/0.071
		Green	-	<b>XA2EA31</b>	0.032/0.071
		Yellow	-	<b>XA2EA51</b>	0.032/0.071
		Blue	-	<b>XA2EA61</b>	0.032/0.071
	- 1	Red	-	<b>XA2EA42</b>	0.032/0.071
<b>Marked</b>					
	1 -	Green	"I"	<b>XA2EA3311</b>	0.032/0.071
	1 -	Black	"↑"	<b>XA2EA3351</b>	0.032/0.071
	1 -	White	"↑"	<b>XA2EA3341</b>	0.032/0.071
	- 1	Red	"O"	<b>XA2EA4322</b>	0.032/0.071
	- 1	Red	"STOP"	<b>XA2EA4342</b>	0.032/0.071

**Mushroom head pushbuttons, spring return**

Shape of head	Type of contacts	Color of push	Diameter Ø (mm)/in.	Reference	Weight kg/lb
	1 -	Black	40/1.575	<b>XA2EC21</b>	0.052/0.115
	1 -	Green	40/1.575	<b>XA2EC31</b>	0.052/0.115
	- 1	Red	40/1.575	<b>XA2EC42</b>	0.052/0.115
	1 -	Yellow	40/1.575	<b>XA2EC51</b>	0.052/0.115
	1 -	Black	60/2.362	<b>XA2ER21</b>	0.058/0.128

Note: Please refer to our website [www.schneider-electric.com](http://www.schneider-electric.com) for information on dimensions

General:  
page 6