

# Control and signaling units Ø 22

Harmony Easy XA2, plastic

Selector switches, with standard or long handle

Key switches

PF132031



XA2ED53

Selector switches, with standard handle or with long handle						
Shape of head	Type of push	Type of contacts		Number and type of positions	Reference	Weight kg/lb
		N/O	N/C			
	Standard handle	1	–	2 - stay put	<b>XA2ED21</b>	0.04/0.088
		1	1	2 - stay put	<b>XA2ED25</b>	0.054/0.119
		2	–	3 - stay put	<b>XA2ED33</b>	0.054/0.119
		2	–	3 - spring return from 2 sides	<b>XA2ED53</b>	0.054/0.119
		1	–	2 - spring return	<b>XA2ED41</b>	0.041/0.090
	Long handle	1	–	2 - stay put	<b>XA2EJ21</b>	0.041/0.090
		1	1	2 - stay put	<b>XA2EJ25</b>	0.041/0.090
		2	–	3 - stay put	<b>XA2EJ33</b>	0.055/0.121
		2	–	3 - spring return from 2 sides	<b>XA2EJ53</b>	0.055/0.121

PF132041



XA2EG03

Key switches						
Shape of head	Type of push	Type of contacts		Number and type of positions	Reference	Weight kg/lb
		N/O	N/C			
	Key	1	–	2 - stay put, one side pull-out	<b>XA2EG21</b>	0.064/0.141
		2	–	2 - stay put, two sides pull-out	<b>XA2EG43</b>	0.078/0.172
		2	–	2 - spring return, one side pull-out	<b>XA2EG63</b>	0.078/0.172
		2	–	3 - spring return from 2 sides, middle pull-out	<b>XA2EG73</b>	0.078/0.172
		2	–	3 - stay put, middle pull-out	<b>XA2EG33</b>	0.078/0.172
		2	–	3 - stay put, 3 sides pull-out	<b>XA2EG03</b>	0.078/0.172

Note: Please refer to our website [www.schneider-electric.com](http://www.schneider-electric.com) for information on dimensions