

Control and signaling units Ø 22

Harmony Easy XA2, plastic

Pushbuttons, push-push

Emergency switching off pushbuttons



XA2EH021

| Pushbuttons, push-push with flush push | | | | | |
|--|------------------|---------------|------------|--------------|--|
| Shape of head | Type of contacts | Color of push | Reference | Weight kg/lb | |
| | N/O N/C | 1 - White | XA2EH011 | 0.04/0.088 | |
| | | 1 - Black | XA2EH021 | 0.04/0.088 | |
| | 1 - Green | XA2EH031 | 0.04/0.088 | | |
| | - 1 Red | XA2EH042 | 0.04/0.088 | | |
| | 1 - Yellow | XA2EH051 | 0.04/0.088 | | |
| | 1 - Blue | XA2EH061 | 0.04/0.088 | | |

| Emergency switching off pushbuttons | | | | | | | |
|-------------------------------------|--------------|------------------|-----------------|---------------------|-----------|--------------|-------------|
| Shape of head | Type of push | Type of contacts | Color of push | Diameter Ø (mm)/in. | Reference | Weight kg/lb | |
| | Push-pull | N/C | Red | 40/1.575 | XA2ET42 | 0.088/0.194 | |
| | | | Turn to release | Red | 30/1.181 | XA2ES442 | 0.056/0.123 |
| | | | | Red | 40/1.575 | XA2ES542 | 0.058/0.128 |
| | | | | Red | 60/2.362 | XA2ES642 | 0.064/0.141 |
| | | | | Black | 30/1.181 | XA2ES422 | 0.056/0.123 |

Note: Please refer to our website www.schneider-electric.com for information on dimensions

Control and signaling units Ø 22

Harmony Easy XA2, plastic

Selector switches, with standard or long handle

Key switches



XA2ED53

| Selector switches, with standard handle or with long handle | | | | | |
|---|-----------------|------------------|----------------------------------|----------------|--------------|
| Shape of head | Type of push | Type of contacts | Number and type of positions | Reference | Weight kg/lb |
| | Standard handle | N/O N/C | 1 - 2-stay put | XA2ED21 | 0.04/0.088 |
| | | | 1 1 - 2-stay put | XA2ED25 | 0.054/0.119 |
| | | | 2 - 3-stay put | XA2ED33 | 0.054/0.119 |
| | | | 2 - 3-spring return from 2 sides | XA2ED53 | 0.054/0.119 |
| | | | 1 - 2-spring return | XA2ED41 | 0.041/0.090 |
| | | | Long handle | 1 - 2-stay put | XA2EJ21 |
| | Long handle | 1 1 - 2-stay put | XA2EJ25 | 0.041/0.090 | |
| | | | 2 - 3-stay put | XA2EJ33 | 0.055/0.121 |
| | | | 2 - 3-spring return from 2 sides | XA2EJ53 | 0.055/0.121 |

| Key switches | | | | | |
|---------------|--------------|------------------|---|-----------|--------------|
| Shape of head | Type of push | Type of contacts | Number and type of positions | Reference | Weight kg/lb |
| | Key | N/O N/C | 1 - 2-stay put, one side pull-out | XA2EG21 | 0.064/0.141 |
| | | | 2 - 2-stay put, two sides pull-out | XA2EG43 | 0.078/0.172 |
| | | | 2 - 2-spring return, one side pull-out | XA2EG63 | 0.078/0.172 |
| | | | 2 - 3-spring return from 2 sides, middle pull-out | XA2EG73 | 0.078/0.172 |
| | | | 2 - 3-stay put, middle pull-out | XA2EG33 | 0.078/0.172 |
| | | | 2 - 3-stay put, 3 sides pull-out | XA2EG03 | 0.078/0.172 |

Note: Please refer to our website www.schneider-electric.com for information on dimensions